



## Acoustic Technologies Electronics Pty Ltd

ABN 40 010 627 997

8-10 Staple Street  
Seventeen Mile Rocks  
Qld 4073 Australia

Telephone (617) 3376 4122  
Fax (617) 3376 5793

PO Box 107  
Sumner Park Qld 4074 Australia

Email [info@atprofessional.com.au](mailto:info@atprofessional.com.au)  
Internet [www.atprofessional.com.au](http://www.atprofessional.com.au)

# SFM24 Wedge Factory Settings

## Active Settings

### LOW SECTION Loudspeaker Management Settings

Output Gain:	+0 dB
Time Delay:	0.217 mSec
Phase:	Normal
High Pass Filter Frequency:	80 Hz
High Pass Filter Type:	24 dB/Octave Linkwitz Riley (6dB Butterworth)
Low Pass Filter Frequency:	1.2 kHz
Low Pass Filter Type:	24 dB/Octave Linkwitz Riley (6dB Butterworth)
Bandpass Filter #1 Frequency:	120 Hz
Bandpass Filter #1 Q:	0.71 Octaves (2)
Bandpass Filter #1 Gain:	+6 dB
Bandpass Filter #2 Frequency:	450 Hz
Bandpass Filter #2 Q:	0.24 Octaves (6)
Bandpass Filter #2 Gain:	+3.5 dB
Bandpass Filter #3 Frequency:	900 Hz
Bandpass Filter #3 Q:	0.48 Octaves (3)
Bandpass Filter #3 Gain:	-2.5 dB

## **HIGH SECTION Loudspeaker Management System Settings.**

Output Gain:	-6.5 dB
Time Delay:	0 mSec
Phase:	Normal
High Pass Filter Frequency:	1.4 kHz
High Pass Filter Type:	18 dB/Octave Butterworth
High Shelf Filter Frequency:	15 kHz
Bandpass Filter Gain:	+8.0 dB
High shelf Type:	12dB/Octave
Bandpass Filter #1 Frequency:	12 kHz
Bandpass Filter #1 Q:	0.71 Octaves (2)
Bandpass Filter #1 Gain:	+5.0 dB